

DT81

Data Logger

dataTaker®

Intelligent Data Logging Products

- USB memory for easy data & program transfer
- Serial 'Smart Sensor' port
- User Definable allocation of memory size & mode
- Web server for browser access
- FTP for automatic data transfer
- Modbus for SCADA connection
- SDI-12 (multiple networks)
- Up to 3 Analog ($\pm 30V$) sensor inputs
- 8 Flexible Digital channels



Specifications

Feature Packed Value for Money!

The *dataTaker DT81* is the answer to the end user or OEM requiring fewer channels whilst demanding the powerful features and flexibility of the *DT80*.

With support for SDI-12 sensors, Modbus for SCADA systems and Web enabled features, the *DT81* is ready to be rolled out into tomorrow's environmental or industrial monitoring projects.

The *DT81* is a robust, stand alone, low power and economical data logger. It's USB memory stick support, 18 bit resolution and extensive communications capabilities make it a powerful partner.

Versatile Measurement

Analog and digital channels, high-speed counter inputs, phase encoder input and programmable serial sensor channel allow the *DT81* to easily connect to most sensors and data measurement sources. Temperature, voltage, current, 4-20mA loops, resistance, bridges, strain gauges, frequency, digital, serial and calculated measurements can all be scaled, logged and returned in engineering units or within statistical reporting. Group sampling, logging, alarm and control tasks within schedules to suit your requirements. Smart sensors, GPS, PLCs and other intelligent devices are supported via a serial sensor port (RS232), with our optional *CANgate* interface available for CAN bus applications.

Superior Data Storage and Communications

Store up to **5 million** data points in user defined memory, log as much or as little as you need with independent control of schedule size and mode. Overwrite or stop logging once allocated memory is full. Archive data on alarm event, copy to USB memory or transfer via FTP, the choice is yours.

Communications features include RS232 with modem support, USB, Ethernet and USB memory stick ports. Connect to the *DT81* locally, remotely or over the Internet. The web server allows browser access to data and files, FTP provides data to your office over the internet or mobile phone network, without the need for polling or specific host software.

Take the next step and experience the *DT81* by contacting your local distributor or *dataTaker* office.

Applications include:

- Research & Development
- Agricultural Research
- Weather Stations
- Total Energy Monitoring
- Environmental Monitoring
- Temperature Profiling
- Aquaculture
- Structural Monitoring
- Strain Gauges
- Process Monitoring
- Fault Identification
- Machine Down Time
- Pressure
- Load Cells
- Flow
- Vehicle Testing
- GPS
- *CANgate* (optional)
 - CAN bus
 - J1939
 - OBDII

Australasia

DataTaker Pty Ltd
7 Seismic Court
Rowville Melbourne
Victoria 3178
Tel: +61 3 9764 8600
Fax: +61 3 9764 8997
Email: sales@datataker.com.au

Europe

Grant Instruments (Cambridge) Ltd
Shepreth
Cambridgeshire
SG8 6GB
Tel: +44 (0) 1763 264780
Fax: +44 (0) 1763 262410
Email: sales@datataker.co.uk

Americas

Computer Aided Solutions
8588 Mayfield Rd, Suite One
Chesterland, OH 44026
Tel: +1 800 9 LOGGER
Tel: +1 440 729 2570
Fax: +1 440 729 2586
Email: sales@computeraidedsolutions.com

FREE
Software &
Technical
Support

www.datataker.com



Analog Inputs

The maximum number of inputs depends on sensor wiring configuration.

Two wire with one shared terminal: 3

Three and Four wire: 1

Fundamental Input Ranges

The fundamental inputs that the DT81 can measure are voltage, current, resistance and frequency. All other measurements are derived from these.

Full Scale	Resolution	Full Scale	Resolution
±30 mVdc	0.25 µV	100 Ω	1.5 mΩ
±300 mVdc	2.5 µV	1000 Ω	15 mΩ
±3 Vdc	25 µV	10,000 Ω	150.00 mΩ
±30 Vdc	250 µV	100 Hz	0.0002 %
±0.3 mA	2.5 nA	10 kHz	0.0002 %
±3 mA	25 nA		
±30 mA	250 nA		

Auto-ranging is supported over 3 ranges.

Accuracy

Measurement at ...	5°C to 40°C	– 45°C to 70°C
DC Voltage	0.1%	0.35%
DC Current	0.15%	0.45%
DC Resistance	0.1%	0.35%
Frequency	0.1%	0.25%

Accuracy table above is % of reading ±0.01% of full scale.

Multiplexer (Input Selector)

Relay Multiplexer

Input impedance:

100KΩ, 1MΩ or >100MΩ, programmable

Common mode range: ±3.5V or ±35V on 30V range

Note: cannot mix low voltage (e.g. thermocouples) with high voltage (e.g. 0-10V) inputs.

Sampling

Sampling for accuracy and noise rejection by integrating over 50/60Hz line period.

Maximum sample speed: 25Hz

Effective resolution: 18 bits

Linearity: 0.01%

Common mode rejection 30mV range: >90dB

Line (50/60Hz) series mode rejection: >35dB

Sensor Excitation

Each channel:

4.5V, 250µA or 2.5mA or Switched external supply.

Sensor Support

Supports a wide range of sensors including, but not limited to, those listed below. A wide range of sensor scaling and linearising facilities including polynomials, expressions and functions.

Thermocouples

Types: B, C, D, E, G, J, K, N, R, S, T

Calibration standard: ITS-90

RTDs

Materials supported: Pt, Ni, Cu

Resistance range: 10Ω to 10KΩ

Thermistors

Types: YSI 400xx Series

Resistance range: <10kΩ,

<20kΩ with parallel resistor

Monolithic Temperature Sensors

Types supported: LM34 - 60, AD590, 592, TMPxx

LM135, 235, 335

Bridge Sensors

Configurations: ¼, ½ & full bridge

Excitation: voltage or current

4-20mA Current Loop

Shunt: Internal 100Ω to a shared common or external shunt resistor.

Digital Channels

Digital Input/Outputs

Number of channels: 4 Bi-directional channels for state & count input or state output.

Input Type: 4 logic level (max: 10Hz, 3 x 30V, 1 x 20V)

Measure state or low speed counts

Low speed counters do not function in sleep mode.

Output Type: 3 with open drain FET (max: 30V, 100mA), 1 with logic output.

Relay Output

1 latching relay (max: 30Vdc, 1A)

Dedicated Counter Inputs

Number: 4 high speed counters or 1 phase encoder (quadrature) inputs (max: 10kHz, 2 x ±30V, 2 x ±10V).

2 Counters have 10mV sensitive inputs for magnetic pick-ups.

Size: 32 bit

SDI-12 Channels

Number: 1 SDI-12 input, shared with digital channel.

Serial Sensor Channel

One channel available and programmable to allow data to be logged from smart sensors and data streams.

Shared with Host Port: RS232 only*

Handshake lines: RTS, CTS

Baud rate: 300 to 115200

**If used as Serial Sensor channel Host Port is not available for other communications.*

Calculated Channels

Combine values from analog, digital and serial sensors using expressions involving variables and functions.

Functions: An extensive range of Arithmetic, Trigonometric, Relational, Logical and Statistical functions are available.

Alarms

Condition: high, low, within range and outside range

Delay: optional time period for alarm response

Actions: set digital outputs, execute any dataTaker command, transmit message.

Scheduling of Data Acquisition

Number of schedules: 11

Schedule rates: 10ms to days

Data Storage

Internal Store

Capacity: 64MB = approx 5,000,000 data points

Removable USB store device (optional accessory)

Types: compatible with USB 1.1 or USB 2.0 drives, e.g. Flash drive.

Capacity: approx. 90,000 data points per megabyte.

Communication Interfaces

Ethernet

Interface: 10BaseT

Protocols: TCP/IP (UDP, FTP, HTTP, Modbus)

RS232

Speed: 300 to 115k baud (57,600 default)

Handshake lines: DCD, DSR, DTR, RTS, CTS

Modem support: auto-answer and dial out

Protocols: PPP, TCP/IP (UDP, FTP, HTTP, Modbus)

USB

USB 1.1, 12Mb/sec – virtual COM port.

Web Server

Built-in pages to view current data and status.

Custom pages can be defined.

Modbus Server (slave)

Access to current data and status.

Available ports, Ethernet, Host Port (RS232)

System

Status Indicators

Status LEDs: 4 for sample, disk, power and attention.

Firmware Upgrade

Via: RS232, Ethernet, USB or USB disk.

Real Time Clock

Normal resolution: 200µs

Accuracy: ±1 min/year (0°C to 40°C), ±4 min/year (-40°C to 70°C)

Power Supply

External voltage range: 10 to 30Vdc

Power Consumption

Normal mode: 5W (15V 330mA)

Charging flat battery: 12W (15V 800mA)

Sleep mode: 3mW (500µA from Internal 6V battery)

Internal Main Battery

Voltage (Capacity): 6V (1.2Ahr) lead acid gel cell

Operating time: continuous sampling: 1 hour

10 minute sampling: 8 days

1 hour sampling: 21 days

Memory and Real Time Clock Battery

Voltage (Capacity): 3.6V (400mAh) lithium, 1/2 AA

Physical and Environment

Construction: Powder coated zinc and anodized aluminum.

Dimensions: 180 x 137 x 65mm

Weight: 1.5kg (4kg shipping)

Temperature range: –45°C to 70°C *

Humidity: 85% RH, non-condensing

*reduced battery life and LCD operation outside range –15°C to 50°C

Accessories Included

Resource CD: includes software, video training and user manual.

Comms cable: USB cable

Line adaptor: 110/240Vac to 15Vdc, 800mA

Training sensor kit

Optional Accessories

A range of accessories are available. Contact your local distributor or visit www.datataker.com

For full technical specifications download the user's manual from our website.

www.datataker.com



Your local distributor

Warranty: The dataTaker DT81 is covered by a 3 year warranty on workmanship and parts.

For further information on the dataTaker range, or for useful downloads, visit the Datataker web site at www.datataker.com or contact your nearest Datataker office or distributor.

Quality Statement: Datataker operates a Quality Management System complying with ISO9001:2000.

It is Datataker's policy to supply customers with products which are fit for their intended purpose, safe in use, perform reliably to published specification and are backed by a fast and efficient customer support service.

Trademarks: dataTaker is a registered trademark of Datataker Pty Ltd.

Specifications: Datataker Pty Ltd reserves the right to change product specifications at any time without notice. Designed and Manufactured in Australia.

dataTaker®